



**Newing-Hall, Inc.**  
16092 King Rd.  
Haskins, OH 43525

---

## **AMC Flash Programmer**

- Step 1- Double click the setup.exe to start the installation
- Step 2- Setup will walk you through the installation
- Step 3- Double click the AMC Programmer icon on your desktop
- Step 4 -Double click the Firmware folder
- Step 5 -Look in: C:\apex\flash\amc1 and click the epc11201.hex then click Open
- Step 6 -Double click the Configuration folder
- Step 7 -Look in: C:\apex\flash\amc1 then clicks the model300.ini then click Open (if you have a 400 or a 600 click on model400 or model 600 rather than model300).
- Step 8- Click on the configuration tab
- Step 9 - Set to the correct COM port (i.e. com 1 or com 2) then set the baud rate to 38400
- Step 10- On the controller: hit ESC then arrow down to Re-Datum hit F1, now arrow down to Load F/W and hit F1 again. The controller should now read Load Firmware
- Step 11- On the controller: hit the Char/Tool Up then arrow up until it reads 38400 then hit ESC
- Step 12- on the computer: press download